

# Distribution Amplifiers



## Larger DigiLink Amplifiers



- Dual input amps, VHF 87-230MHz, UHF 470-790MHz
- Distribute signal from your digibox or \*TV and radio aerial
- 9V DC on every output to power DigiLink eyes
- Return path for IR control



**LDL212R**  
2-in, 12-out mains powered  
DigiLink amp



**LDL216R**  
2-in, 16-out mains powered  
DigiLink amp

\* Suitable for digital TV signal distribution Ch21-60 from a satellite receiver or from an aerial fitted with a 4G filter.

	LDL212R	LDL216R
Number of inputs	2	2
Number of outputs	12	16
Frequency range	87-230 & 470-790MHz	
Gain	8dB	8dB
Noise figure	Typ. <4dB	Typ. <4dB
Max output level (IMA3 -60dB)	84dB $\mu$ V	84dB $\mu$ V
Isolation between outlets	22dB	22dB
Return path range	5-30MHz	
Return path gain	6dB	6dB
Power for DigiLink eyes	9V 15mA short circuit protected	
RED, EMC and LVD	Compliant	
Power required	220-240V~50/60hz <3W	