

C-TEC Economy Fire Panels

PRODUCT OVERVIEW

Introducing a new range of Economy panels from C-TEC!

The new-look super-enhanced CFP Economy conventional fire panel offers an array of user and installer-friendly features at a very competitive price.

Supplied in an attractive flush or surface mountable plastic enclosure, 2, 4 and 8 zone versions are available, each featuring four conventional sounder circuits, class change and alert inputs and combined keypad/keyswitch entry.

Comprehensive test and fault finding facilities are also provided.

PRODUCT FEATURES

- Intuitive user-friendly interface with colour-coded buttons and combined keypad/keyswitch entry to access level 2
- Third-party certified to EN54-2/4 by the LPCB
- 2, 4 or 8 zone circuits (dependent on model purchased)
- Four conventional sounder circuits
- Integral 1.5A EN54-4/A2 compliant switch mode PSU
- Two open-collector outputs (Remote and Reset)
- 'Class change' and alert inputs
- Installer-friendly design accommodates easy first fix and straightforward maintenance
- Attractive flush or surface mountable plastic lid and enclosure - no bezel required
- Low quiescent current
- Multiple indicators
- End of line units included (one per zone)
- Requires 2 x B/12V/3.2AH/SLA batteries

BEAM DEVICES

C-TEC's Economy panels are also compatible with Conventional Beam and Self adjusting beam devices see [page 66](#)



SOUNDERS & VISUAL INDICATORS

See [Pages 48-49](#)



Please note batteries are not included: 2, 4 & 8 Zone panels require 2x B/12V/3.2AH/SLA - listed below

SPECIFICATION

Construction	Polycarbonate enclosure
Enclosure Finish	RAL7035 Textured
Panel Dimensions	380mm (W) x 235mm(H) x 96mm(D) 2, 4 & 8 panels have the same measurements
Weight	1.75 Kg (without batteries)

COMPATIBLE DEVICES



DETECTORS

Apollo protocol Series 65 - see [page 46](#).
C-Tec Activ Detectors - see [page 58](#).



CALL POINTS

Apollo protocol Series 65 - see [page 46](#).



ASPIRATING EQUIPMENT

Use in conjunction with Vesda Aspiring equipment on [pages 72-73](#) to protect small businesses of less than 250m² and 500m²



PLEASE NOTE: This panel does not have the functions to do the following:

- Delay zones or outputs
- Set up coincidence between zones
- Make zones non latching
- Have volt free contacts for fire or fault. You would need to add E/15/A relays for fire and fault

PLEASE SEE SCIMITAR PANEL FOR FULL FUNCTION PANEL- See [page 46](#)

PANELS

F/CHSC/2/E	CFP Economy 2 zone panel, keypad/keyswitch entry, does not extend (requires 2 x B/12V/3.2AH/SLA battery)
F/CHSC/4/E	CFP Economy 4 zone panel, keypad/keyswitch entry, does not extend (requires 2 x B/12V/3.2AH/SLA battery)
F/CHSC/8/E	CFP Economy 8 zone panel, keypad/keyswitch entry, does not extend (requires 2 x B/12V/3.2AH/SLA battery)

BATTERIES

B/12V/3.2AH/SLA	12 Volt 3.2Ah sealed lead acid battery (1 block)
-----------------	--