



To be read in full before installation
and kept for future reference

Operating Instructions USB Charging Socket Outlets

S1288	Slimline
S12882	Slimline OB Rockers
SD1288	Slimline Décor
SD22882	Slimline Décor OB Rockers
8668	Slimline Screwless

VC1288	Vimark Curve
M1288	Metalclad
8168	Ultra Flatplate
8568	Ultra Screwless
S1455	Slimline Part M OB Rockers

Safety Instructions	Product Features
<ul style="list-style-type: none"> Always switch off the electrical supply before commencing installation Connect to a 240V ac electrical supply This socket and metal back boxes must be earthed Only suitable for indoor use Note: The front surface of this product may become warm in use The USB ports are for charging information technology equipment only There is restricted bottom cable entry access in 25mm back boxes This socket must be installed in accordance with the current edition of the IET Wiring Regulations and Building Regulations, BS 7671 <p>REMOVE THIS PRODUCT FROM THE INSTALLATION BEFORE CARRYING OUT INSULATION RESISTANCE TESTING</p> <p>If in doubt, contact a qualified electrician</p>	<ul style="list-style-type: none"> 13A SP Switched Socket complete with 3 USB (2 Type A + 1 Type C) Charging Ports This USB Charger is compatible with portable devices such as smart phones, tablets and other such devices that require charging via a USB type A and Type C ports The USB ports deliver up to 4.0A simultaneously charging current across the 3 ports Each port can deliver a maximum of 3A charging current These ports use auto detection IC technology to detect the connected devices and optimises high-speed charging between the ports depending on the devices connected Standard Slimline and Curve ranges fit into 25mm flush and dry lining boxes (restricted bottom cable entry access). Ultra-ranges and sockets with outboard rockers require a 35mm back box.

Specification

USB Output (total)	4.0A max. at 5V shared	13A Socket Current Rating	13A
Voltage	240V ac 50Hz	Compliance	BS 1363:Pt 2

Deta Electrical Company Limited

UK: Panattoni Park Luton Road Chalton Bedfordshire LU4 9TT
EU: Unit 16 Ashbourne Ind. Est. Ashbourne Co. Meath A84 W972
deta.co.uk | Technical Helpline: +44(0)1582 544 548

