



JF12504SM



JFG416U

Cable Capacity

20A = 16mm ²
32A = 16mm ²
63A = 25mm ²
100A = 95mm ² = M8 Lug
125A = 95mm ² = M8 Lug
160A = 95mm ² = M8 Lug
200A = 240mm ² = M10 Lug
250A = 240mm ² = M10 Lug
315A = 240mm ² = M10 Lug
400A = 240mm ² = M10 Lug
630A = 2 x 300mm ² = M12 Lug
800A = 2 x 300mm ² = M12 Lug

Spare Fuse types

20A = NIT20
32A = NIT32
63A = TIS63
100A = TCP100
125A = TF125
160A = TF160
200A = TF200
250A = TKF250
315A = TKF315
400A = TMF400
630A = TTM630
800A = TLM800

Fuse Combination Switches 20 - 800A

Characteristics

- Provides individual protection and control of circuits.
- Enclosures up to 100A have been designed to provide adequate cabling space without the need for additional cable spreader boxes.
- Operation of the device is through a door mounted rotary handle which is mechanically interlocked to prevent access to live conductors when the switch is in the on position. The handle is padlockable in the off position.
- All versions will accept standard BS 88 fuse links and can be converted to switch disconnector by fitting copper links.

Utilisation category

- AC22B - 630 - 800A
- AC23A - 20 - 630A

Product features

- Conforms to: BS EN 60947-3
- Rated IP31.

Note: Maximum rated fuse links are fitted in all fuse combination switches.

Note: Copper links for conversion to isolating switches

- For dimensions see page 88.
- For technical information see page 89.

Description	Cat ref.	Cat ref. Cable extension boxes if required
Fuse Combination Switches Single Pole & Switched Neutral		
20A Fuse Combination Switch SP&SN	JFB202U	-
32A Fuse Combination Switch SP&SN	JFB203U	-
63A Fuse Combination Switch SP&SN	JFD206U	-
100A Fuse Combination Switch SP&SN	JFE210U	JZA701
Fuse Combination Switches Triple Pole & Neutral		
20A Fuse Combination Switch TP&N	JFB302U	-
32A Fuse Combination Switch TP&N	JFB303U	-
63A Fuse Combination Switch TP&N	JFD306U	-
100A Fuse Combination Switch TP&N	JFE310U	JZA701
125A Fuse Combination Switch TP&N	JFG312U	JZA701
160A Fuse Combination Switch TP&N	JFG316U	JZA701
200A Fuse Combination Switch TP&N	JFG320U	JZA701
250A Fuse Combination Switch TP&N	JFG325U	JZA701
315A Fuse Combination Switch TP&N	JFH331U	JZA702
400A Fuse Combination Switch TP&N	JFH340U	JZA702
630A Fuse Combination Switch TP&N	JFI363U	JZA703
800A Fuse Combination Switch TP&N	JFI380U	JZA703
Fuse Combination Switches Triple Pole & Switched Neutral		
20A Fuse Combination Switch TP&SN	JFB402U	-
32A Fuse Combination Switch TP&SN	JFB403U	-
63A Fuse Combination Switch TP&SN	JFD406U	-
100A Fuse Combination Switch TP&SN	JFE410U	JZA701
125A Fuse Combination Switch TP&SN	JFG412U	JZA701
160A Fuse Combination Switch TP&SN	JFG416U	JZA701
200A Fuse Combination Switch TP&SN	JFG420U	JZA701
250A Fuse Combination Switch TP&SN	JFG425U	JZA701
315A Fuse Combination Switch TP&SN	JFH431U	JZA702
400A Fuse Combination Switch TP&SN	JFH440U	JZA702
630A Fuse Combination Switch TP&SN	JFI463U	JZA703
800A Fuse Combination Switch TP&SN	JFI480U	JZA703
Copper Links		
63A	JC60L	-
100A	JC10L	-
125 / 200A	JC20L	-
315 / 400A	JC40L	-
630A	JC63L	-