

**Description**

The Hager range of fuse combination switches provides individual protection and control of circuits.

The enclosures up to 100A have been designed to provide adequate cabling space without the need for additional cable spreader boxes.

Operation of the device is through a door mounted rotary handle which is mechanically interlocked to prevent access to live conductors when the switch is in the on position. The handle is padlockable in the off position.

All versions will accept standard BS 88 fuse links and can be converted to switch disconnector by fitting copper links.

**Utilisation category**

AC22B - 630 - 800A  
AC23A - 20 - 630A

**Product features**

Complies with:  
BS EN 60947-3  
IP31.

**Note:** Maximum rated fuse links are fitted in all fuse combination switches.

**Cable Capacity**

20A	= 16mm <sup>2</sup>
32A	= 16mm <sup>2</sup>
63A	= 25mm <sup>2</sup>
100A	= 95mm <sup>2</sup>
125A	= 95mm <sup>2</sup>
160A	= 95mm <sup>2</sup>
200A	= 240mm <sup>2</sup>
250A	= 240mm <sup>2</sup>
315A	= 240mm <sup>2</sup>
400A	= 240mm <sup>2</sup>
630A	= 2 x 300mm <sup>2</sup>
800A	= 2 x 300mm <sup>2</sup>

For dimensions see page 3.65.

For technical information see page 3.66.



JFD206U



JFG416U

**Fuse Combination Switches Single Pole and Switched Neutral**

Description	Cat ref.	Cat ref. Cable extension boxes if required
20A Fuse Combination Switch SP&SN	JFB202U	-
32A Fuse Combination Switch SP&SN	JFB203U	-
63A Fuse Combination Switch SP&SN	JFD206U	-
100A Fuse Combination Switch SP&SN	JFE210U	JZA701

**Fuse Combination Switches Triple Pole and Neutral**

20A Fuse Combination Switch TP&N	JFB302U	-
32A Fuse Combination Switch TP&N	JFB303U	-
63A Fuse Combination Switch TP&N	JFD306U	-
100A Fuse Combination Switch TP&N	JFE310U	JZA701
125A Fuse Combination Switch TP&N	JFG312U	JZA701
160A Fuse Combination Switch TP&N	JFG316U	JZA701
200A Fuse Combination Switch TP&N	JFG320U	JZA701
250A Fuse Combination Switch TP&N	JFG325U	JZA701
315A Fuse Combination Switch TP&N	JFH331U	JZA702
400A Fuse Combination Switch TP&N	JFH340U	JZA702
630A Fuse Combination Switch TP&N	JFI363U	JZA703
800A Fuse Combination Switch TP&N	JFI380U	JZA703

**Fuse Combination Switches Triple Pole and Switched Neutral**

20A Fuse Combination Switch TP&SN	JFB402U	-
32A Fuse Combination Switch TP&SN	JFB403U	-
63A Fuse Combination Switch TP&SN	JFD406U	-
100A Fuse Combination Switch TP&SN	JFE410U	JZA701
125A Fuse Combination Switch TP&SN	JFG412U	JZA701
160A Fuse Combination Switch TP&SN	JFG416U	JZA701
200A Fuse Combination Switch TP&SN	JFG420U	JZA701
250A Fuse Combination Switch TP&SN	JFG425U	JZA701
315A Fuse Combination Switch TP&SN	JFH431U	JZA702
400A Fuse Combination Switch TP&SN	JFH440U	JZA702
630A Fuse Combination Switch TP&SN	JFI463U	JZA703
800A Fuse Combination Switch TP&SN	JFI480U	JZA703

**Copper Links**

For conversion to isolating switches

63A	JC60L
100A	JC10L
125 / 200A	JC20L
315 / 400A	JC40L
630A	JC63L