

Timers & switches

Illuminated Push Button timer



Illuminated Push Button Timer
Timers & switches

Illuminated Push Button Timer - Timers & switches

A stylish, illuminated push button timer suitable for retrofit into any wiring system. Provides energy saving functionality by turning off the power source via timer, to avoid unnecessary power usage. The push button timer can be used in conjunction slave devices for multi-way applications. A Capacitor must be used in the circuit when switching low wattage loads such as fluorescent, compact fluorescent, and LEDs.

Key Features

- 16A any load type
- Blue Locator ring
- One minute countdown LED indicator
- Re-set timing sequence at any time during countdown
- Can be interlinked with any Elkay slave switches (Only one master per circuit)
- Fits into 25mm depth back boxes
- Time settings from 2 mins to 2 hours

3875A-1

- 3 wire (Live, switch live and neutral required)

Typical applications:

- Commonly used to control all loads and appliances in any room (except bedrooms)
- Suitable for lighting, heating and ventilation systems

350A-1

- 2 wire (Live and switch live required)
- A 24 hour uninterrupted supply is required
- No neutral required
- Intelligent power search function

Typical applications:

- Commonly used to control lighting in corridors and stairwells
- Can be used as a 1 way switch to control room lighting
- Suitable for lighting (Instant start or hot re-strike only)

350A-3

- 3 core - Live, switch live and trigger required (Switch live optional if blue ring indicator is not required)
- No Neutral required
- Slaves must be used when more than one switch is required in circuit and must be wired in three core to an Elkay master timer from the illuminated range. Only one master per circuit. All other switches must be slaves.

Typical applications:

- Commonly used to control lighting in corridors and stairwells with the master push button timer

Illuminated Push Button Timer - Technical specification

Part No.	Type	Configuration	Finish	Rating	GID
3875A-1***	Illuminated Push Button Timer Master	3 Wire	White	16A-240V	7TCA299010R0045
350A-1***	Illuminated Push Button Timer Master	2 Wire* for lighting only	White	16A-240V	7TCA299010R0011
350A-3	Illuminated Push Button Timer Slave	3 Core**	White	16A-240V	7TCA299010R0014

*PFCC-1 Capacitor will often be required when switching certain types of load - see Section 3/15 for full details or contact Elkay Technical

Slaves must be used with illuminated range and connected with 3 Core cables to Master unit. *Slave unit required for multiway switching See Technical Section 6/4 & 6/6 for wiring diagrams