


Product Description: BatPac[™]CWS Colour & Wattage Switchable 1800mm Batten


Offering 36 product combinations in one, this modular plug and play linear is colour switchable between 3000K, 4000K and 6500K, plus has a choice of wattage between 34W and 62W. Modular emergency packs and microwave sensors are available to purchase separately making the product perfect for the wholesaler to control stock levels and store less products, whilst also being simple for the contractor to convert on site.

SKU Code	Wattage	ColorTemp	Lumens	BeamAngle	SKUType	FinishColor
AU-BA1862CWS	34	3000K	4800	120	Non Dimmable	White
AU-BA1862CWS	34	4000K	5100	120	Non Dimmable	White
AU-BA1862CWS	34	6500K	4800	120	Non Dimmable	White
AU-BA1862CWS	62	3000K	8400	120	Non Dimmable	White
AU-BA1862CWS	62	4000K	9000	120	Non Dimmable	White
AU-BA1862CWS	62	6500K	8400	120	Non Dimmable	White


Line Drawing



Polar Curve



Colour



White

Feature & Benefits

- Colour switchable between 3000K, 4000K and 6500K
- IK08 rated
- -20 - +45° ambient operating temperature
- Opal polycarbonate diffuser for even light distribution
- Can be surface mounted or suspended
- Plug and play emergency, emergency self test and microwave sensing packs available
- 5 Year Warranty

Product Specs:

Input Voltage	220~240V AC	Input Frequency	50/60HZ
IP Rating	IP20	Lifetime L70 (hrs)	50000hrs
IK Rating	IK08	Lamp Base	Other
Width (mm)	61	Length (mm)	1734
Height (mm)	71	Product Type	Linears
Operating Temp. (Min) °C	-20°C	Operating Temp. (Max) °C	45°C

Compliance & Approvals:



Warranty:

This product has a warranty period of 5 Years. Warranties may be available on certain products as indicated in the product description. Warranties are valid from the date of purchase. The warranty is invalid in the case of improper use, installation, tampering, removal of the Q.C. date label or installation in an improper working environment or installation. Should this product fail during the warranty period it will be replaced free of charge, subject to the correct installation of the original product and subsequent return of the faulty unit. Aurora does not accept responsibility for any installation costs associated with the replacement of this product and Aurora reserves the right to alter specifications without prior notice.