

# **20A Double Pole Switches**

# • • •

### Description

This stylish range is easy to install, with coloured terminals, clear white terminal markings and the frontplates are supplied in protective bags.

### **Features**

- Complete with surface mounting box
- Selected products available with and without knockouts in mounting box
- Clear terminal markings
- Terminals have large lead-ins
- Neon versions available
- Neon leads enclosed
- Recessed earth bar
- Captive and backed out terminal screws
- Red flagged switch indicator
- 2 earth terminals
- 25-year guarantee

### Range

- 0-	
Back boxes with knockouts	
1 gang 20A DP switch	M1213
1 gang 20A DP switch with neon	M1214
1 gang 20A DP switch with flex outlet	M1214FL
Back boxes without knockouts	
1 gang 20A DP switch with neon	M1314

## **Technical Specification**

Voltage rat	ing	250Vac	
Current Rating		See range table	
Contact gap	)	3mm	
Size	1g	78mm x 78mm	
Depth		46mm	

No user serviceable parts

BS EN 60669-1 : 2000

### **Back Boxes**

### All knockouts are 20mm diameter

	Back boxes with		Back boxes without	
	knockouts		knockouts	
	Sides	Back	Sides	Back
1g	5	1	0	1

# Terminal Capacity

	2.5mm <sup>2</sup>	4mm²	6mm²	10mm²
L & N	4	2	1	1

**Standards** 

•