

# LED FLEXI-STRIP

## PULSE 12VDC LED FLEXI-STRIP



RGB - Hand Held Remote



Driver



RGB - Infra Red Receiver

## PULSE 12VDC 24W LED FLEXI-STRIP

- Suitable for use in bars & clubs, restaurants, under counter displays, hotel/office receptions, showrooms, exhibition stands, step lighting, window dressing
- 5m roll of flexi striplight
- Strip can be cut every 3 LEDs
- Each kit c/w driver, flex & 3M double sided tape for easy installation
- RGB kit with receiver and hand held remote controller

DIMENSIONS(mm)	Length	Depth
R5MSIK-WW	5,000	10
R5MSIK-CW	5,000	10
R5MSIK-RGB	5,000	10

	Warm White	Cool White	RGB
	R5MSIK-WW	R5MSIK-CW	R5MSIK-RGB
<b>Total Power (W):</b>	24	24	24
<b>Total Light Output (lm):</b>	1,250	1,500	N/A
<b>Lifetime (hrs):</b>	30,000	30,000	30,000
<b>CCT (K):</b>	3500	5000	N/A
<b>CRI (Ra):</b>	70	70	70
<b>Power Factor (PF):</b>	0.7	0.7	0.7
<b>Weight (kg):</b>	0.3	0.3	0.3



**Note:** It is not recommended to join PULSE flexi-strip. Off-cuts cannot be re-used as power supply units are not available separately. ROBUS VEGAS flexi-strip should be used if joining or use of off-cuts with power supply units are required.

