

Simple set reader / keyfob



- Up to 4 Simple Set readers per panel
- No Master Keyfob for ease of programming
- Can be mixed with Accenta keypads
- Relay output for keyswitch input panels
- Up to 8 Keyfobs per Reader
- Full mimic of panel / keypad sounds

Reader

Operating Voltage	11 to 15V from Panel	Reading Distance	Nominally 20mm
Current Consumption	100mA max	Relay Contacts	100mA max current capability
Construction	White 2mm ABS	Dimensions (h x w x d)	84 x 118 x 22mm

Keyfob

Power	Inductively powered (no batteries)	Material	Polycarbonate
-------	------------------------------------	----------	---------------

Part No	Description	Part No	Description
SS/01	Reader with 2 keyfobs	SS/F	Keyfob

8EP407N-UK Pet Tolerant Kit



1x 8SP399A-UK Accenta Mini Gen4 control panel with LCD keypad
3x 8IR103 Activ8 pet tolerant PIR sensors
2x AC035 Door contacts
1x AC030 Panic button
1x AC066 100m 6 core cable
1x 8EP420 Reson8 bell box
1x UL1213 1.2Ah battery

Specifications	Optima Compact Gen4	Accenta Gen4 / Metal Gen4	Accenta Mini Gen4
On board keypad & display	Yes	No	No
Simple Set Interface	Yes		
RKP Indication	Yes (not supplied)	Yes (supplied)	
8 Zones	+ve loop, fully programmable		
Tamper	-ve loop global		
PA	-ve loop		
Bell Output	12V latching, timed 1 to 99 minutes		
Strobe Output	12V		
Extension Speaker	Max two 16 Ohm		
Entry/Exit Timers	Programmable 10 to 990 seconds		
Zone Input Delay	300 or 800ms selectable		
Set +ve Output	Source 10mA, sink 40mA		
CPU Current consumption (standby)	55mA	45mA	
RKP Current consumption (standby)	25mA		
Low voltage output	13V +/- 5%		
Rechargeable battery	Up to 2.1Ah	Up to 7Ah	Up to 2.1Ah
Communicator outputs	No	Yes	Yes
Communicator output types	Intruder, PA, Fire, Abort, Set		
PCB Fuses	1 x 1.6A, 3 x 1.0A		
Mains input fuse	125mA anti-surge		
Total current output	1 Amp when supported by fully charged battery		
Mains supply voltage	230V +/- 10%		
RKP wiring	6 core Max distance 100m		
Dimensions CPU (h x w x d)	200 x 253 x 55mm	230 x 290 x 80mm (Accenta Gen4) 255 x 300 x 85mm (Accenta Metal Gen4)	200 x 253 x 55mm

For more information:

Visit www.honeywell.com/security/uk

Fax: +44 (0) 1698 738300

Email: HSUK64SalesTeam@Honeywell.com

Honeywell Security Group

Newhouse Industrial Estate
Motherwell, Lanarkshire, ML1 5SB
Scotland

Tel: +44 (0)1698 738200

Fax: +44 (0)1698 738300

www.honeywell.com

HSC-GEN4-02-EN(0610)SB-E
June 2010

© 2010 Honeywell International Inc.

Honeywell