

# Ei128RBU



## Relay Module With Battery Back-up



- Triggers external devices if the alarms on the system are activated, such as a strobe light
- Mains powered with Rechargeable Lithium Back-up
- Volt free contacts, rated 5A
- Additional connectors for ease of wiring
- Compatible with 3000, 2110e, 160e and 140RC Series alarms

### Description

The Ei128RBU Relay Module is designed to fit under 3000, 2110e, 160e and 140RC Series Alarms and can be used to trigger external devices, such as a strobe light or telecare system, if the interconnected alarms in the system activate

### Technical

<b>Supply Voltage (V)</b>	230	<b>Voltage Type</b>	AC
<b>Battery Type</b>	Lithium rechargeable	<b>Power Consumption (W)</b>	0.8

### Dimensions & Weights

<b>Depth (mm)</b>	32	<b>Height (mm)</b>	143
<b>Width (mm)</b>	143	<b>Product weight (kg)</b>	0.186
<b>Packaged weight (kg)</b>	0.219		

### Approvals & Warranty

<b>Certification/Approvals</b>	EN 60065:2014, EN 61000-6-1:2007, EN 61000-6-2:2005	<b>Warranty</b>	5 year warranty
<b>EAN Number</b>	5099383004014		

### Environmental

<b>Humidity Range (%)</b>	15-95	<b>Temperature Range (°C)</b>	-10 to 40
---------------------------	-------	-------------------------------	-----------